

# 632 Series

## 2 Amp Power Controllers



Access control system power requirements are uniquely different from other systems. Unlike camera system power requirements, access control systems draw more current for locking hardware and during access control-related events. 75 – 85% of access control operating problems and technical support calls are due to power issues.\* Access control systems require steady and clean (filtered) low-voltage DC current with surge suppression to protect printed circuit boards and connected devices from damage due to dirty power (transients and voltage spikes).

SDC power supplies have been developed specifically to help reduce power system issues and to support electric locks and access control requirements. Our hybrid design combines the efficiency of switching power supplies with the inductive load handling capability of linear power supplies in various 12/24 VDC current output capabilities and enclosure sizes. Filtering and output voltage regulation provide protection and ensure the longevity of all system components.

The high performance, heavy-duty circuitry is ideal for inductive loads and multi-door applications. With the addition of SDC programmable controllers or relay modules, the user-friendly modular designs ensure versatility, interface capability and easy installation of virtually any electric locking devices, access controls and related fire & life safety equipment.

\* SDC technical support logs.



### MODELS

**632RF** 2 Amp DC Power Controller With Cabinet

**632RFA** 2 Amp DC Power Controller With Large Cabinet



### STANDARD FEATURES

- Regulated and filtered linear DC power
- Class 2 output
- Field selectable dual voltage
- Fire/emergency release input
- Isolated battery charging circuit
- Low battery disconnect
- Input and output surge protection
- Visual status indicator (LED)
- Cabinet enclosures with pre-configured control module mounting holes



### OPTIONAL FEATURES

- 230 VAC, 50/60 Hz input
- Key lock cover
- Fire/emergency release manual reset switch
- System on/off switches
- Choice of compatible door control modules



## APPLICATIONS

### FIRE/EMERGENCY RELEASE INPUT

A fire alarm input provides simultaneous release of all fail safe locks and door holders in case of an emergency. An optional manual reset switch following a fire/emergency release or power loss is available to meet code compliance. When the optional manual reset feature is required, should an AC power loss occur or the emergency release input be actuated, personnel must restore secondary output power manually at the power supply after the emergency release signal is reset and/or AC power is restored.

### ISOLATED BATTERY CHARGING CIRCUIT

A separate charging output provides 13.5 or 27 volts to fully charge the batteries. The secondary output is always precisely maintained at 12 or 24VDC to protect locking devices and components from over voltage while the batteries are charging. The specified secondary output current is also maintained while batteries are charging. Derating of the secondary output current is not required when charging batteries.

### LOW BATTERY DISCONNECT

Batteries are disconnected from the output circuit prior to deep discharge, preventing battery destruction. Batteries are not included and should be ordered separately.\*

### DOOR CONTROL MODULES

Door control relay modules are available to meet virtually any application need. All wiring for lock hardware, access controls, remote controls and monitoring is terminated at one central location. Installation and troubleshooting is simplified. Modules may be factory installed or ordered separately for field installation as needed. Cabinet enclosures are pre-configured with mounting holes to accommodate door control modules. All modules are individually fused for protection of multiple station systems.

\* See related products for backup batteries.

### INPUT & OUTPUT SURGE PROTECTION

Input and output surge protection is built-in. The AC input voltage is circuit breaker protected and the outputs are PTC protected.

### VISUAL STATUS INDICATOR (LED)

LED tri-color status indicators provide information regarding the AC input, DC output and battery backup status. Outputs for remote annunciation are available.

### SYSTEM ON/OFF SWITCHES

Optional System On/Off switches are available both inside the cabinet enclosure or on the cabinet enclosure cover.


### KEY LOCK COVER

Optional key lock cover available where tamper-resistance is required.

### INTERNATIONAL STANDARD INPUT

Additionally an alternative 230VAC international standard input is an available option.

## CROSS REFERENCE



	<b>602</b>	<b>631</b>	<b>632</b>	<b>634</b>	<b>636</b>
<b>DC Output Rating</b>	1 Amp	1.5 Amp	2 Amp	4 Amp	6 Amp
<b>Small Cabinet</b>	602RF	631RF	632RF	-----	-----
<b>Large Cabinet</b>	602RFA	631RFA	632RFA	634RFA	636RFA
<b>Less Cabinet</b>	602RFL	631RFL	632RFL	-----	-----
	<a href="#">CLICK TO VIEW</a>	<a href="#">CLICK TO VIEW</a>		<a href="#">CLICK TO VIEW</a>	<a href="#">CLICK TO VIEW</a>

# SPECIFICATIONS

	632RF	632RFA
<b>Input</b>	115 VAC 800 mA 50/60 Hz	115 VAC 800 mA 50/60 Hz
<b>Output</b>	12/24 VDC 2 Amp	12/24 VDC 2 Amp
<b>Battery Charger</b>	13.5/27 VDC 250 mA	13.5/27 VDC 250 mA
<b>Cabinet</b>	12" x 12" x 4" 20 Guage	16" x 14" x 6½" 16 Guage
<b>Weight</b>	9 lbs	20 lbs

## BACKUP BATTERY DISCHARGE TIME

Standby Power	12 VDC			
<b>Battery</b>	RB12V4	RB12V4	RB12V4	RB12V4
<b>Battery Qty*</b>	1	2	3	4
<b>Current Load</b>	Power Backup Time (Hours)			
250 mA	19.6	49.4	84.8	124.4
500 mA	7.8	19.5	33.5	49.2
750 mA	4.5	11.3	19.5	28.6
1 Amp	3.1	7.7	13.3	19.4
1.5 Amp	1.8	4.5	7.7	11.3
2 Amp	1.2	3.1	5.2	7.7

Standby Power	24 VDC**	
<b>Battery</b>	RB12V4	RB12V4
<b>Battery Qty*</b>	2	4
<b>Current Load</b>	Power Backup Time (Hours)	
250 mA	19.6	49.4
500 mA	7.8	19.5
750 mA	4.5	11.3
1 Amp	3.1	7.7
1.5 Amp	1.8	4.5
2 Amp	1.2	3.1

[CLICK TO VIEW](#)

## DOOR CONTROL MODULE CAPACITY\*\*\*

Power Supply	632RF		632RFA	
<b>Battery Qty*</b>	0-2	3-4	0-2	3-4
<b>VR</b>	1	1	1	1
<b>ACM</b>	2	2	2	2
<b>EMC</b>	1	1	2	1
<b>FB</b>	2	2	2	2
<b>UR1</b>	4	2	4	2
<b>CR</b>	2	1	2	1
<b>UR2</b>	-----	-----	2	1
<b>UR4</b>	-----	-----	2	1
<b>IPDC</b>	-----	-----	1	-----
<b>IPDS</b>	-----	-----	1	-----

[CLICK TO VIEW](#)

\* Battery quantity based on size of SDC's RB12V4 backup batteries.

\*\* For 24 VDC standby power, minimum order of (2) batteries. Batteries must be ordered in pairs.

\*\*\* Total combined load of modules and access control hardware may not exceed power supply rating.

## CERTIFICATIONS

- UL 1012 Power Units Other Than Class 2
- CSA-C22.2 No. 107.1 Power Conversion Equipment
- UL 2043 Fire Test for Heat and Visible Smoke Release for Discrete Products and Their Accessories Installed in Air-Handling Spaces

## HOW TO ORDER

### FOLLOW STEPS FOR ORDERING

 Designates optional step

<p>1  SPECIFY MODEL</p> <p><b>632RF</b> 2 Amp DC Power Controller With Cabinet</p> <p><b>632RFA</b> 2 Amp DC Power Controller With Large Cabinet</p>				
<p>2  SPECIFY OPTIONS</p> <p><b>220</b> 230 VAC, 50/60 Hz</p> <p><b>KL</b> Key Lock Cover</p> <p><b>MR</b> Fire/Emergency Release Manual Reset Switch</p>		<p>4  SPECIFY BOARDS</p> <p><b>VR</b> Voltage Control Regulator, 12VDC</p> <p><b>ACM</b> Six Station Input Control Relay</p> <p><b>EMC</b> Exit Device Sequencer</p> <p><b>FB</b> Multiple Fused Output Relay</p> <p><b>UR1</b> Microprocessor Controller, Two Relays</p> <p><b>CR</b> Four Station Control Relay</p> <p><b>UR2*</b> Microprocessor Controller, Four Relays</p> <p><b>UR4*</b> Microprocessor Controller, Eight Relays</p> <p><b>IPDC*</b> IPPro Controller, VR Included</p> <p><b>IPDS*</b> IPPro Door Expansion, VR Included</p> <p><small>*UR2, UR4, IPDC and IPDS boards can only be accommodated in the RFA large cabinet enclosure.</small></p>		
<p>3  SPECIFY ON/OFF</p> <p><b>PS1</b> Power On/Off Inside Cabinet Enclosure</p> <p><b>PS1A</b> Power On/Off On Cabinet Enclosure Cover</p>				
STEP NUMBER:	1	2	3	4
ORDERING EXAMPLE:	<b>632RFA</b>	<b>KL MR</b>	<b>PS1A</b>	<b>UR1 UR2</b>

## RELATED PRODUCTS

**632RFL** 2 Amp DC Power Controller Less Cabinet



### BACKUP BATTERIES

SDC power supplies equipped with batteries provide continuous operation of access controls, locking devices and peripheral components during a power failure.

[CLICK TO VIEW](#)

**RB12V4** 12V/5Ah Battery

**RB12V4-2** 12V/5Ah Battery, Qty 2 Pack

**RB12V7** 12V/7Ah Battery

**RB12V7-2** 12V/7Ah Battery, Qty 2 Pack

